

# Настройка роутера Huawei HG231F-1

Для доступа к web - интерфейсу роутера в адресной строке браузера необходимо ввести **192.168.1.100** и нажать **Enter**.

В открывшемся окне необходимо авторизоваться. Данные по умолчанию **Имя пользователя — админ, Пароль — админ**. Далее нажмите кнопку **Вход**.

После чего в меню слева выбираем раздел **Basic** и подраздел **WAN**. Затем устанавливаем галочки на пунктах **WAN connection – Enable** и **Service List – INTERNET**, в пункте **Connection type** устанавливаем **PPPoE**, в пункте **NAT** устанавливаем **Enable**, в поле **Username** вводим **Логин** по договору Дом.ру, в пункте **Password** вводим **Пароль** по договору Дом.ру. Нажимаем **Submit**.

Basic > WAN

WAN

Name	Connection Type	Connection Status	IP Address	Enable	Remove
WAN1_INTERNET_R_ETH1					

WAN1\_INTERNET\_R\_ETH1

WAN connection:  Enable

Service list:  INTERNET  TR069

Bind list:  LAN1  LAN2  LAN3  LAN4  
 SSID1  SSID2  SSID3  SSID4

Connection type: PPPoE

NAT: Enable

Authentication mode: Auto

Connection trigger: AlwaysOn

User name: login

Password: \*\*\*\*\*

MTU: Auto Size: 1492

MAC Address Clone:  Enable

MAC Address: [ ][ ][ ][ ][ ][ ] Clone My PC's MAC

Submit

# Настройка Wi-Fi сети.

Слева выбираем раздел **Basic** и подраздел **WLAN**. Устанавливаем галочку на пункте **Enable WLAN**. Затем в поле **Mode** выбираем **802.11 b/g/n**, **SSID index** указываем **SSID1**, в поле **SSID** указываем **Имя** беспроводной сети, ставим галочку на пункте **Enable SSID – Enable**, **Security mode** устанавливаем **WPA-PSK/WPA2-PSK**, в пункте **WPA Pre-Shared Key** указываем **Пароль** от wi-fi сети. Нажимаем кнопку **Submit**.

The image shows a screenshot of a router's web interface for configuring WLAN settings. The breadcrumb navigation is 'Basic > WLAN > WLAN'. The left sidebar has 'Basic' selected, and 'WLAN' is highlighted in red. The 'WLAN' tab is active, and the 'Enable WLAN' checkbox is checked. The 'Wireless Settings' section is highlighted with a red box and contains the following configuration:

Mode:	802.11b/g/n
Country Code:	RUSSIA
Channel:	Auto
MCS:	Auto
Band Width:	20/40 MHz
Guard Interval:	long
Transmit power:	20 dBm (1-20 dBm)*
SSID Index:	SSID1
SSID:	TTK *
Maximum Number of Accessing Devices:	16 *
Enable SSID:	<input checked="" type="checkbox"/> Enable
Hide Broadcast:	<input type="checkbox"/> Enable
Enable WMM:	<input checked="" type="checkbox"/> Enable
Security Mode:	WPA-PSK/WPA2-PSK
WPA Pre-Shared Key:	***** *
WPA Encryption:	AES
Enable WPS:	<input type="checkbox"/> Enable

The 'Submit' button at the bottom right is also highlighted with a red box.